

Express Mail Label No.: EL 395673011 US

Date of Deposit: May 23, 2001

Atty Docket No.: 2001 P 09460 US

IN THE  
UNITED STATES PATENT AND TRADEMARK OFFICE

This is a U.S. Patent Application for:

Title: METHOD AND APPARATUS FOR AUTOMATICALLY GENERATING  
COMMON PARADIGMS IN COMPUTER SUPPORTED TELEPHONY  
APPLICATIONS (CSTA) PROTOCOLS

Inventor #1: Mark Bernard Hettish

Address: 112 Kingussie Ct.  
Cary, NC 27511

Citizenship: USA

09863912-052301

IN THE UNITED STATES  
PATENT AND TRADEMARK OFFICE  
PATENT APPLICATION

5 METHOD AND APPARATUS FOR AUTOMATICALLY GENERATING COMMON  
PARADIGMS IN COMPUTER SUPPORTED TELEPHONY APPLICATIONS  
(CSTA) PROTOCOLS

BACKGROUND OF THE INVENTION

10

1. Field of the Invention

The invention relates to methods and apparatus  
for implementing computer supported telephony  
applications. More particularly, the invention relates  
15 to method and apparatus for automatically generating  
common paradigms in computer supported telephony  
applications (CSTA) protocols.

2. Brief Description of the Prior Art

20 It is well known in the art to couple a  
computer to a PBX switch in order to provide enhanced  
telephony services. Such services include voice mail,  
fax on demand, text to speech email retrieval, call  
forwarding, interactive voice response systems, etc.  
25 Most of these applications are built around the CSTA  
standard which is a standard for the protocols used  
across the link between a computer and a PBX switch. The  
CSTA standard protocols utilize ASN.1, Abstract Syntax  
Notation number One, an international standard for  
30 specifying data used in communication protocols.  
Although ASN.1 is powerful, it is a complex language.

00863912-052301  
TOP SECRET

The CSTA standard has been implemented in various proprietary PBX-Computer interfaces such as the "Call Bridge for Work Groups" which is the interface used in the Siemens Hicom 300 PBX.

5

Although the CSTA has made the development of telephony application somewhat uniform, the protocols provided by the CSTA are relatively low level. Even with the "Call Bridge for Work Groups" interface, a telephony application must take responsibility for many low level functions of the interface. For example, even using the "Call Bridge for Work Groups" interface, an application must take responsibility for creating, maintaining, and tearing down a TCP/IP socket connections; building and parsing the ASN. 1 encoded CSTA stream; handling the reception system status heartbeat messages; sending and handling the result of System Status heartbeat messages; and managing the generation and timing of invoke Ids. In addition, many applications would also want to add diagnostic user interface features to indicate status, statistics and errors as they pertain to a particular connection. All of these functions must be implemented by the application. Many of these, such as the ASN.1 builder/parser are time-consuming and/or costly to develop/purchase.

10

15

20

25

09863912.052301  
T0650"269860

It is known in the art to provide a higher level interface to some of the "Call Bridge for Work Groups" - CSTA interface. An earlier Siemens product provided limited ActiveX support for the following CSTA Services: Monitor Start, Monitor Stop, Divert Call, System Status Filter; and the following CSTA Events: connected, conferenced, connection cleared, delivered, diverted, established, held, agent logged off, agent logged on, network reached, agent not ready, queued, agent ready, retrieved, service initiated, transferred, agent work not ready, agent work ready, call info, system status, and universal failure error. However, there have not been any full high level interfaces addressing all of the features and events of the "Call Bridge for Work Groups" - CSTA interface. Moreover, there have not been any high level interface which aid in creation of common paradigms used in telephony applications. Furthermore, there have not been any high level interfaces which aid in the provision of diagnostic functions in telephony applications.

**SECRET**

5

10

15

20

25

It is still another object of the invention to provide a control interface which is easily configurable

It is another object of the invention to provide a control interface which facilitates the easy creation of user interfaces.

5 It is still another object of the invention to provide a control interface which provides easy to use diagnostic interfaces.

In accord with these objects which will be  
10 discussed in detail below, the control interface according to the invention utilizes component based interface objects such as Microsoft ActiveX or Sun Microsystems JavaBeans to provide a high level interface to all of the "Call Bridge for Work Groups" - CSTA  
15 protocols. The presently preferred embodiment of the invention utilizes ActiveX. ActiveX controls generally include properties, methods, and events. According to the invention, the properties interface is used to set and get configuration values; the methods interface is  
20 used to initialize and shut down the control interface as well as to send CSTA messages to the control interface; and the events interface is used to transfer asynchronous data including CSTA events, data within events, CSTA responses, system status CSTA requests, and other control  
25 notifications. Property pages are also provided for implementing user interfaces and diagnostics. The control interface permits the automatic generation of common paradigms including: invoke ID generation, invoke

ID timing, send heartbeat messages, and reply to heartbeat messages.

5 The control interface maintains a rich set of statistics including messages/sec, number of requests, number of responses, number of events, number of errors and number or rejects. All are tabulated on the incoming and outgoing link and all are displayable via a property page. Statuses are also displayable via a property page.

10 Errors are logged internally by the control interface and can be displayed via a property page. Moreover, the control interface provides an ActiveX method by which applications can log error information including application defined error strings that are displayable

15 via a property page.

#### BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a high level block diagram of the platform architecture according to the invention including, the Call Bridge - CSTA interface of a PBX switch, the control interface of the invention, and an application generically referred to as a Tserver; and

25 FIG. 2 is a high level block diagram of the control architecture of the invention illustrating the flow of data between the control interface of the invention and the Call Bridge - CSTA interface of a PBX switch.

## DETAILED DESCRIPTION

Turning now to Figure 1, a platform  
5 architecture according to the invention includes the Call  
Bridge interface 10 of a PBX switch, the control  
interface 12, and a telephony application 14 referred to  
herein as Tserver.

10 As mentioned above, the control interface 12 is  
preferably an ActiveX control that provides property,  
method and event interfaces to the application 14 on one  
side and a CSTA interface to Call Bridge 12 on the other  
side. In addition, property pages 16 are preferably  
15 provided to support such items as configuration, status  
and statistics viewing and error viewing as described in  
more detail below.

The control interface 12 communicates with the  
20 Call Bridge 10 using the CSTA protocol via a TCP/IP based  
socket connection 18. As an ActiveX control, the control  
interface 12 provides three interfaces to the Tserver 14.  
These interfaces include the properties interface 20, the  
methods interface 22, and the events interface 24. The  
25 properties interface 20 is used to set and get  
configuration values. The methods interface 22 is used  
to initialize the control interface 12, shutdown the  
control interface 12 and to send CSTA messages to the



control interface 12. The events interface 24 is used by the control interface 12 to send asynchronous data to the Tserver 14. These data include CSTA events (including data within the events), CSTA responses, the System Status CSTA request and any other notifications that the control interface 12 needs to send. Property pages 16 are provided and can be activated by the Tserver application via the appropriate method calls.

Referring now to Figure 2, the internal architecture of the control interface 12 is shown surrounded by phantom lines. The main processing component 26 handles any set and get property requests 20. It also handles methods 22, those related to initialization and shutdown as well as those related to sending CSTA services. Where needed it will use the ASN.1 parser 28 and builder 30 to receive and send CSTA messages from/to the Call Bridge CSTA interface. According to the presently preferred embodiment, the Main Processing 26 and ASN.1 components 28, 30 are implemented as part of the main thread of an ActiveX dynamically linked library (DLL).

As illustrated in Figure 2, all communications between the Call Bridge CSTA interface 18 and the main processing 26 is via the Winsock DLL 32. A socket connection is established upon which ASN.1 encoded CSTA messages are sent and received to and from the Call

Bridge CSTA interface. According to the invention, a receive thread 34 will wait on the socket for a signal that indicates an incoming ASN.1 encoded CSTA message. When such a message is received, the receive thread 34 will post a message to the main thread and control is passed to the main thread. The main thread reads the CSTA message from the socket. The message is then parsed by the ASN.1 parser component 28. Data from the parsed message is then sent to the Tserver 14 along with the notification of the arrival of the message. This is preferably accomplished in a single event call.

According to the presently preferred embodiment, the ASN.1 builder and parser components  
15 utilize the same Open Source Solutions (OSS components) as the Call Bridge CSTA interface.

The control interface is preferably based on the MFC environment, utilizes an InprocServer32 type of  
20 ActiveX control, and supports the ActiveX apartment  
threading model. It will be appreciated that MFC based  
ActiveX controls must fire events from the main thread.  
This requirement is the reason the receive thread 34  
merely posts a message to the main thread 26 instead of  
25 handling the parsing of the message and the firing of the  
event itself.

098691-052301  
T02250"2T6E9860

The control interface according to the invention is preferably implemented with the Microsoft Developer studio through which a library of C-language files are compiled. The following discussion includes a description of the various, properties, methods, events, and pages defined by the invention to implement the control interface.

#### 10 Properties

The following are the major properties are used by the present invention: Call Bridge CSTA Port Number, Call Bridge CSTA Server Name, Control ID, and Error logging.

The port number is a numeric representation of the Call Bridge CSTA port to which the control interface connects. The server name is a string that contains the host file name of the Call Bridge CSTA server. This scheme requires that an entry be made in the host file that contains the Call Bridge CSTA server name and its associated IP address.

25 If the Tserver allows server name entry then the person running the application must know the Call Bridge CSTA server name. If the Tserver application does not allow server name entry then whatever hard coded

value it uses must be the name that is used in the host file.

5       The Control ID is a string that identifies the type of the control interface. For this control interface, the string is **CallBridge CSTA for Tservers** and is read-only.

10       The error logging property is a Boolean value that indicates whether or not the control interface should send internal error events to the application. These events are used to allow for debugging of the control interface. The default value of this property signifies that events should not be sent to the  
15       application.

20       The control interface provides two methods for managing the control: one to initialize the connection and one to tear down the connection.  
ControlOpenConnection() calls to FireControlConnectionOpen() and ControlCloseConnection() calls to FireControlConnectionClosed().

25       In order to allow applications to differentiate between versions of the invention a new version property is used. The code for this property is similar to that of the Control ID Property with a BSTR value of the

format <major version>.<minor version>.

According to the invention an option is provided for the control interface to send system status heartbeats to Callbridge CSTA and track the system status responses. This option is controlled via a new property, the heartbeat property.

The Heartbeat property is similar to the Error Logging property, and includes a Boolean flag that enables or disables the heartbeat. The default is disabled. This property is persistent.

The heartbeat implementation performs the following actions when enabled. After 30 seconds of inactivity on the incoming link it sends a System Status Enabled to Callbridge CSTA. If the reply comes within 10 seconds then it starts the inactivity timer again. If the reply does not come within 10 seconds then it sends the FireControlLinkClosed() event. Timers 1 and 2 are reserved for heartbeat timer usage.

The present invention supports timed requests. If a response does not come back within a certain period of time an event will be fired indicating this condition. Timed requests are implemented as properties. These properties allow the user to enable request timing and to set the number of seconds that the control is to wait

before deeming that a response has been lost. The first property enables or disables the timing of requests. The second property assigns the time to wait for a response. This property will accept values from 10 seconds to 60 seconds. The maximum of 60 seconds is partially determined by the implementation, system timers can only accept up to a maximum of 64 seconds. The lower threshold of 10 is to avoid values that can easily cause necessary timeouts under certain load conditions. Each of these properties is persistent.

The internal invoke ID manager returns invoke IDs in the range of 100 to 0xFFFF (the UINT maximum). This value is then directly used as the timer ID for the SetTimer() routine. Timer values 1-99 are reserved for possible future timer usages within the control interface.

When a request is about to be sent, a timer is started with a timer ID equal to the invoke ID. The period of the timer is set from the Timed Requests property value. When a response, error, or reject is received, the parsed invoke ID (which equals the timer ID) is passed to the KillTimer() routine and no action is taken. If a timer times out, a message is sent to the WindowProc() with one of the parameters containing the timer ID (invoke ID). In this situation, KillTimer() is called to free the timer and an event is sent that

contains the invoke ID. The event that will be used is FireUniversalError() with a class of **performance\_errors** and a value of **performanceLimitExceeded**.

## 5 Methods

The control interface supplies methods for CSTA service support as well as other peripheral support needed.

10 It supports CSTA services via the following methods. All methods return the Invoke ID of the request if they complete without any errors. Any negative value indicates an error condition.

15 MonitorStart()  
MonitorStop()  
DivertCall(), includes divert type and private user data parameter  
SystemStatus(), includes cause parameter

20 AlternateCall(), includes device ID to toggle, current call ID, and held call ID  
AnswerCall(), includes answering call ID and answering device ID  
25 ChangeMonitorFilter(), includes xref id, call filter, agent filter, feature filter, and maintenance filter  
ClearConnection(), includes call ID to clear, device ID to clear

0986393-052301  
T0E250"2T6E9860

- ConferenceCall(), includes held call ID, held device ID, active call ID, and active device ID
- ConsultationCall(), includes held call ID, held device ID, called device ID, private user-user data length, and private user-user data
- 5 GenerateDigits, includes calling device ID and digits
- HoldCall(), includes call ID and device ID
- MakeCall(), includes originating device ID, called device ID, and auto-answer mode.
- 10 ReconnectCall(), includes cleared call ID, cleared device ID, retrieved call ID, and retrieved device ID
- RetrieveCall(), includes call ID and device ID
- RouteTrigger(), includes device ID and trigger
- RouteSelect(), includes xref ID and device ID
- 15 RejectCall(), includes xref ID
- RouteEnd(), includes xref ID
- SingleStepTransfer(), includes active call ID, active device ID, transfer to device ID, private user-user data length, and private user-user data
- 20 SnapshotDevice(), includes device ID
- TransferCall(), includes held call ID, held device ID, active call ID, active device ID

According to the presently preferred

25 embodiment, query device requests are handled via separate methods, one for each type of query as listed below.



- QueryDeviceDoNotDisturb(), includes device ID  
QueryDeviceFowarding(), includes device ID  
QueryDeviceDeviceInfo(), includes device ID  
5 QueryDeviceAgentState(), includes device ID

According to the presently preferred embodiment, set feature requests are handled via separate methods, one for each type of feature as listed below.

10

- SetFeatureGroupAgent(), includes device ID and state  
SetFeatureDoNotDisturb(), includes device ID and state  
SetFeatureForwarding(), includes device ID, type,  
forwarding DN, private type, private DN, and private  
15 system forwarding type  
SetFeatureAgentState(), includes device ID, state, and  
group

Several services support optional parameters.

- 20 According to the presently preferred embodiment of the invention, the parameters are handled in the following manner.

- call ID - For any service that supports an optional call  
25 ID, the application should pass the value LONG -1 to indicate that the call ID is not present.

user-user data - For any service that supports user-user data a length parameter will also be provided. A 0 length parameter indicates that the user-user data is not present.

auto answer flag - This parameter is required on the make call request.

10 filter - The optional filter parameter of the monitor  
start request is not exposed to the application. The  
application should use change monitor filter in order to  
change this value.

15           The invention provides some unique parameter  
types for services as described below.

user-user data - This field is thought of as a data byte stream. However, data byte streams are not easily passed between the application and Active-X controls. For this reason it is required that the application store the user-user data into a string (type BSTR in the control definition). The control interface treats it not as a string but as a byte array of data that is as long as the accompanying length that the application has passed in.

device IDs - If a device ID is a dialable number it is passed in as the ASCII representation of that dialable number. If a device ID is a device number it is passed

in as the '#' followed by the ASCII representation of the device number.

The invention supports the following new  
5 service responses: `SystemStatusResponse()` which includes  
invoke ID.

The invention supports the following additional  
methods which are used to enable and disable the  
10 filtering of System Status requests that are received  
from Callbridge.

`ControlSystemStatusFilterStart()`  
`ControlSystemStatusFilterStop()`

15

The invention supports the following additional  
methods which are used to connect to and disconnect from  
the Callbridge gateway.

20 `ControlOpenConnection()`  
`ControlCloseConnection()`

The invention also provides a new method which  
is used to enable an application to log errors.  
25 Application generated errors are logged in the control  
error log and displayable with the control error log  
viewer.

0986391-052301  
FOE50" 216E9860



user-user data length, private user-user data, private trunk, and private ACD DN

FireDiverted(), includes diverted call ID, diverted  
5 device ID, diverting device ID, destination device ID,  
local connection state, and cause

FireEstablished(), includes answered call ID, answered  
device ID, answering device ID, calling device ID, called  
10 device ID, last redirect device ID, private held call ID,  
local connection state, and cause

FireHeld(), includes held call ID, held device ID,  
holding device ID, local connection state, cause, and  
15 private cause

FireNetworkReached(), includes call ID, device ID, trunk,  
called device ID, local connection state, and cause

20 FireQueued(), includes queued call ID, queued device ID,  
queue device ID, calling device ID, called device ID,  
last redirect device ID, private held device ID, local  
connection state, and cause

25 FireRetrieved(), includes retrieved call ID, retrieved  
device ID, retrieving device ID, local connection state,  
and cause

09063912.052304  
T02250.212304

FireServiceInitiated(), includes new call ID, new device ID, requested device ID, and local connection state

- 5 FireTransferred(), includes primary old call ID, primary old device ID, secondary old call ID, secondary old device ID, transferring device ID, transferred-to device ID, new call ID, new device ID, local connection state, cause, private cause, private user-user data length, and  
10 private user-user data

FireAgentLoggedIn(), includes agent device ID, agent ID, and group ID

- 15 FireAgentLoggedOff(), includes agent device ID, agent ID, and group ID

FireAgentReady(), includes agent device ID

- 20 FireAgentNotReady(), includes agent device ID

FireAgentWorkNotReady(), includes agent device ID

FireDoNotDisturb(), includes device ID and state

25

FireFailed(), includes call ID, device ID, called device ID, local connection state, and cause

0986394.052301  
"0E250" 2169860

FireForwarding() - device ID, forward type, forward DN,  
private forward type, private forward DN

- 5 FireOriginated() - originating call ID, originating  
device ID, called device ID, local connection state,  
cause

Several events support optional parameters.

- 10 These parameters are handled in the following manner.

Local connection state - The value SHORT -1 is returned  
if this optional field is not present.

- 15 cause - The value SHORT -1 is returned if this optional  
held is not present.

private cause - The value SHORT -1 is returned if this  
optional field is not present.

20

immediate connect to agent flag - This field supports  
three values: SHORT 0 indicates a FALSE condition, SHORT  
1 indicates a TRUE condition, and SHORT -1 indicates a  
not present condition.

25

ANI flag - This field supports three values: SHORT 0  
indicates a FALSE condition, SHORT 1 indicates a TRUE  
condition, and SHORT -1 indicates a not present

condition.

trunk number - The value LONG -1 is returned if this optional held is not present.

5

private forwarding type - This field supports three values: SHORT 0 indicates a FALSE condition, SHORT 1 indicates a TRUE condition, and SHORT -1 indicates a not present condition.

10

private forwarding DN - The value "" (a NULL string) is returned if this optional field is not present.

15

ACD DN - The value "" (a NULL string) is returned if this optional field is not present.

device IDs - In any instance where the dialable number or device number is not present the value "" (a NULL string) is returned.

20

The invention provides the following unique parameters for events.

25 user-user data - This is the same as the parameter described above with regard to services.



conference list - This parameter is encoded in the following format: <ASCII call ID>,<ASCII device ID>/<ASCII call ID>,<ASCII device ID>/...

5

device IDs - If a device ID is a dialable number it is returned as the ASCII representation of that dialable number. If a device ID is a device number it is returned as the '#' followed by the ASCII representation of the device number.

The invention supports control events via the following ActiveX events.

15           The following events are used to indicate  
System Status filtering conditions.

```
FireControlFilterStartResult()
FireControlFilterStopResult()
```

20

The following events are used to indicate the status of the connection to Callbridge.

```
FireControlConnectionOpen()
```

```
25 FireControlConnectionClosed()
```



FireUniversalError(), passes back the class and value values instead of just a single error code. The Invoke ID is also passed back.

5

FireReject(), passes back the class and value values instead of just a single error code. The Invoke ID is also passed back.

10 FireAlternateCallResult()

FireAnswerCallResult()

15 FireChangeMonitorFiiterResult(), includes call filter, agent filter, feature filter, and maintenance filter

FireClearConnectionResult()

20 FireConferenceCallResult(), includes new call ID and new device ID

FireConsultationCallResult(), includes new call ID and new device ID

25 FireGenerateDigitsResult()

FireHoldCallResult()

09863912 052301  
"09863912 052301"

FireMakeCallResult(), includes new call ID and new device ID

5 FireQueryDoNotDisturbResult(), includes state

FireQueryFowardingResult(), includes type count, type list, DN list, private type count, private type list, and private DN list

10

FireQueryDeviceInfoResult(), includes device ID, type, private type, private sub-type, private attribute, and calls queued

15 FireQueryAgentStateResult(), includes state, agent ID, group

FireReconnectCallResult()

20 FireRetrieveCallResult()

FireSetFeatGroupAgentResult()

FireSetFeatDNDResult()

25

FireSetFeatFwdResult()

FireSetFeatAgentStateResult()

FireSingleStepXferStateResult(), includes transferred  
call ID and transferred device ID

FireSnapshotDeviceResult(), includes call ID 1 through  
5 call ID 5 and local connection state 1 through local  
connection state 5

FireSystemStatusResult()

10 FireTransferCallResult(), includes new call ID and new  
device ID

The invention provides the following unique  
parameters for responses.

15

DN lists - The query device forwarding response may  
contain two DN lists, one for each forwarding type  
present and one for each private forwarding type present.  
The DN list format is the ASCII equivalent of the device  
20 ID separated by commas with each double entry followed by  
a single slash: <ASCII device ID>/<ASCII device ID>/...

type lists - The query device forwarding response may  
contain up to 20 different forwarding types. Normally  
25 these would be represented each as a separate short  
parameter but Active-X controls have a limit and do not  
allow 22 parameters to be passed back in events. Because  
of this, the forwarding types and the private forwarding



As mentioned above, the invention supports  
ActiveX apartment threading. This is implemented via the  
following code:

5  
BOOL  
CChCstaCtrl::CChCstaCtrlFactory::UpdateRegistry(BOOL bRegi  
ster)  
{  
10 // TODO: Verify that your control follows apartment-model  
threading rules.  
// Refer to MFC TechNote 64 for more information.  
// If your control does not conform to the  
apartment-model rules, then  
15 // you must modify the code below, changing the 6th  
parameter from  
// afxRegApartmentThreading to 0.  
if (bRegister)  
return AfxOleRegisterControlClass(  
20 AfxGetInstanceHandle(),  
m\_clsid,  
m\_lpszProgID,  
IDS\_CBCSTA,  
IDB\_CSTA,  
25 afxRegApartmentThreading,  
\_dwChCstaOleMisc,  
\_tlid  
\_wVerMajor,

5                   \_wVerMinor);  
else  
                  return AfxOleUnregisterClass(m\_clsid,m\_lpszProgID);  
}

                  Apartment threading allows multiple instances  
of a control within a single process. When instantiated  
in this manner, each instance of the control will attempt  
to form a separate connection with a Callbridge server.

10 By using the server name and port properties on each  
control it is possible to have controls within the same  
process connects as different hosts connected to the same  
Callbridge server or different hosts connected to  
different Callbridge servers.

15

#### Property Pages

                  According to the invention, support has been  
added to collect a number of different statuses and  
20 statistics. All statuses and statistics to be kept are  
defined below and are displayable via new property pages.  
The purpose of these property pages are to provide  
methods for allowing a quick glance at items that show  
how the control interface is operating. These pages are  
25 mainly intended for support purposes. According to the  
presently preferred embodiment, four property pages are  
provided: the link status page, the statistics page, the  
error viewing property page, and the configuration





2. Heartbeats Acked - number of heartbeat messages acknowledged,

3. Heartbeats Failed - number of heartbeat messages not acknowledged.

5

The link status property page has a Clear button that will clear all the above items except the Link Statuses and Event Acceptance State. According to the presently preferred embodiment, all items on the link status property page are updated every 10 seconds.

The statistics property page includes the following information:

1. CSTA Requests, responses, errors, rejects and events received,
2. CSTA Requests, responses, errors, rejects and events sent,
3. Messages per second received,
4. Messages per second sent.

20

The statistics property page has a Clear button that will clear all the above items. According to the presently preferred embodiment, all items on the statistics property page are updated every 10 seconds.

25

Before discussing the error viewing page, the error logging according to the invention will be discussed. According to the invention, internal errors

may be sent to an application via events if the error the logging property is set to TRUE. In addition a simple error log is maintained.

5           The `su_log_message()` takes error message information and writes an ASCII representation to a circular file. This implementation has the following characteristics: The file has a fixed size. The file resides in the system directory. The file will is named  
10 `CSTA_TSERVER_ERROR_LOG.LOG`. The file will is viewable via a simple text editor. The file is viewable via the error log property page.

          If error logging is implemented, a property  
15 page is provided that allows a user to view the error log. The error viewing property page has the following characteristics:

1. Error entries are displayed in a tree view  
20 format,
2. Error details are expandable/contractible,
3. A refresh button allows the display to be refreshed.

          In addition, the following strings are used by the  
25 error viewing property page:

`IDS CBCSTATSERVER PPG ERROR VIEW Error Viewing Property Page`

`IDS CBCSTATSERVER PPG ERROR VIEW CAPTION Error Viewing`

The configuration property page provides an interface for setting and viewing all properties. This property page displays all properties and allows  
5 read/write properties to be changed. The following strings will be created for this property page.

IDS CBCSTATSERVER PPG CONFIG

IDS CBCSTATSERVER\_PPG\_CONFIG\_CAPTION

10           There have been described and illustrated herein methods and apparatus for a control interface for CSTA protocols. While particular embodiments of the invention have been described, it is not intended that the invention be limited thereto, as it is intended that  
15 the invention be as broad in scope as the art will allow and that the specification be read likewise. It will therefore be appreciated by those skilled in the art that yet other modifications could be made to the provided invention without deviating from its spirit and scope as  
20 so claimed.

TOP SECRET 000000000000